

Control Commands

Model No. PT-FRQ60



- Please refer to the Operating Instructions for the serial command format, limitations, connection and other details.
- シリアルコマンドのフォーマット、制限事項、接続方法およびその他詳細につきましては、各モデルの取扱説明書をご覧ください。
- 有关串行控制命令的格式、限制事项、连接方法以及其他详情、请参阅各机型的使用说明书。

Panasonic

| CATEGORY | FUNCTION | Parameter/Name | Sub-Parameter | CONTROL | | QUERY | | FRQ50 SERIES |
|-----------------------------------|-------------------------------|----------------|----------------------|----------------------|-------------------|------------------|-------|--------------|
| | | | | COMMANDS/CALL BACK | COMMANDS | CALL BACK | FRQ60 | |
| BASIC OPERATION REMOTE CONTROL | POWER | ON | | PON | QPW | 001 | | ✓ |
| | | OFF (STANDBY) | | POF | | 000 | | ✓ |
| | VOLUME | UP | | AUU | | | | ✓ |
| | | DOWN | | AUD | | | | ✓ |
| | INPUT SELECT | COMPUTER1 | | IIS:RG1 | QIN | RG1 | | ✓ |
| | | HDMI1 | | IIS:HD1 | | HD1 | | ✓ |
| | | HDMI2 | | IIS:HD2 | | HD2 | | ✓ |
| | | DIGITAL LINK | | IIS:DL1 | | DL1 | | ✓ |
| | INPUT SELECT (DIGITAL LINK) | COMPUTER1 | | IIS:DL1:PC1 | QIN | DL1:PC1 | | ✓ |
| | | COMPUTER2 | | IIS:DL1:PC2 | | DL1:PC2 | | ✓ |
| | | VIDEO | | IIS:DL1:VID | | DL1:VID | | ✓ |
| | | HDMI1 | | IIS:DL1:HD1 | | DL1:HD1 | | ✓ |
| | | HDMI2 | | IIS:DL1:HD2 | | DL1:HD2 | | ✓ |
| | | S-VIDEO | | IIS:DL1:SVD | | DL1:SVD | | ✓ |
| | FREEZE | OFF | | OFZ:0 | QFZ | 0 | | ✓ |
| | | ON | | OFZ:1 | | 1 | | ✓ |
| | MENU KEY | | | OMN | | | | ✓ |
| | RETURN KEY | | | OBK | | | | ✓ |
| | ENTER KEY | | | OEN | | | | ✓ |
| | UP KEY | | | OCU | | | | ✓ |
| | DOWN KEY | | | OCD | | | | ✓ |
| | LEFT KEY | | | OCL | | | | ✓ |
| | RIGHT KEY | | | OCR | | | | ✓ |
| | DEFAULT KEY | | | OST | | | | ✓ |
| | AUTO SETUP KEY | | | OAS | | | | ✓ |
| | SHUTTER | OFF | | OSH:0 | QSH | 0 | | ✓ |
| | | ON | | OSH:1 | | 1 | | ✓ |
| | SHUTTER(Toggle) | OFF | | OSH | QSH | 0 | | ✓ |
| | | ON | | | | 1 | | ✓ |
| | FUNCTION KEY | | | FC1 | | | | ✓ |
| | SYSTEM SELCTOR KEY | | | OSL | | | | ✓ |
| | ASPECT KEY | | | VS1 | | | | ✓ |
| | ECO | | | OEC | | | | ✓ |
| | NUMERIC KEY | 0 | | ONK:0 | | | | ✓ |
| | | 1 | | ONK:1 | | | | ✓ |
| | | 2 | | ONK:2 | | | | ✓ |
| | | 3 | | ONK:3 | | | | ✓ |
| | | 4 | | ONK:4 | | | | ✓ |
| | | 5 | | ONK:5 | | | | ✓ |
| | | 6 | | ONK:6 | | | | ✓ |
| | 7 | | ONK:7 | | | | ✓ | |
| | 8 | | ONK:8 | | | | ✓ | |
| | 9 | | ONK:9 | | | | ✓ | |
| STATUS KEY | | | STS | | | | ✓ | |
| DIGITAL LINK KEY | | | DLK | | | | ✓ | |
| INPUT MENU KEY | | | IPT | | | | ✓ | |
| SCREEN ADJUSTMENT | | | OSA | | | | ✓ | |
| AUDIO MUTE | OFF | | AMT:0 | QMT | 0 | | ✓ | |
| | ON | | AMT:1 | | 1 | | ✓ | |
| SELF DIAGNOSIS | | | | QVX:ERRS1 | ERRS1=***** | | ✓ | |
| PICTURE | PICTURE MODE | DYNAMIC | | VPM:DYN | QPM | DYN | | ✓ |
| | | NATURAL | | VPM:NAT | | NAT | | ✓ |
| | | STANDARD | | VPM:STD | | STD | | ✓ |
| | | CINEMA | | VPM:CIN | | CIN | | ✓ |
| | | GRAPHIC | | VPM:GRA | | GRA | | ✓ |
| | | DICOM SIM. | | VPM:DIC | | DIC | | ✓ |
| | | REC709 | | VPM:709 | | 709 | | ✓ |
| | CONTRAST | +1 | | VCN:001 | QVR | 001 | | ✓ |
| | | +63 | | VCN:063 | | 063 | | ✓ |
| | BRIGHTNESS | +1 | | VBR:001 | QVB | 001 | | ✓ |
| | | +63 | | VBR:063 | | 063 | | ✓ |
| | COLOR | +1 | | VCO:001 | QVC | 001 | | ✓ |
| | | +63 | | VCO:063 | | 063 | | ✓ |
| | TINT | +1 | | VTN:001 | QVT | 001 | | ✓ |
| | | +63 | | VTN:063 | | 063 | | ✓ |
| | SHARPNESS | 0 | | VSR:000 | QVS | 000 | | ✓ |
| | | 15 | | VSR:015 | | 015 | | ✓ |
| | WHITE GAIN | 0 | | VWH:00 | QWH | 00 | | ✓ |
| | | 10 | | VWH:10 | | 10 | | ✓ |
| | COLOR TEMPERATURE | USER1(USER) | | OTE:04 | QTE | 4 | | ✓ |
| | | USER2 | | OTE:09 | | 9 | | ✓ |
| | | DEFAULT | | OTE:10 | | 10 | | ✓ |
| | | 3200K | | OTE:3200 | | 3200 | | ✓ |
| | | 3300K | | OTE:3300 | | 3300 | | ✓ |
| | | 9200K | | OTE:9200 | | 9200 | | ✓ |
| | | 9300K | | OTE:9300 | | 9300 | | ✓ |
| | | 9400K | | OTE:9400 | | 9400 | | ✓ |
| | | 12900K | | OTE:12900 | | 12900 | | ✓ |
| | | 13000K | | OTE:13000 | | 13000 | | ✓ |
| | COLOR TEMP-NAME SETTING USER1 | COLORTEMP1 | | VXX:NCGS1=COLORTEMP1 | QVX:NCGS1 | NCGS1=COLORTEMP1 | | ✓ |
| | COLOR TEMP-NAME CLEAR USER1 | COLORTEMP1 | | VXX:NCLI1=+00000 | | | | ✓ |
| | WHITE BALANCE LOW-RED | -127 | | VOR:001 | QOR | 001 | | ✓ |
| | WHITE BALANCE LOW-GREEN | -127 | | VOG:001 | QOG | 001 | | ✓ |
| | | +127 | | VOG:255 | | 255 | | ✓ |
| | WHITE BALANCE LOW-BLUE | -127 | | VOB:001 | QOB | 001 | | ✓ |
| | | +127 | | VOB:255 | | 255 | | ✓ |
| | WHITE BALANCE HIGH-RED | 0 | | VHR:000 | QHR | 000 | | ✓ |
| | | +255 | | VHR:255 | | 255 | | ✓ |
| | WHITE BALANCE HIGH-GREEN | 0 | | VHG:000 | QHG | 000 | | ✓ |
| | | +255 | | VHG:255 | | 255 | | ✓ |
| WHITE BALANCE HIGH-BLUE | 0 | | VHB:000 | QHB | 000 | | ✓ | |
| | +255 | | VHB:255 | | 255 | | ✓ | |
| GAMMA | 1.0 | | VGA:1.0 | QGA | 1.0 | | ✓ | |
| | 1.8 | | VGA:1.8 | | 1.8 | | ✓ | |
| | 2.0 | | VGA:2.0 | | 2.0 | | ✓ | |
| | 2.1 | | VGA:2.1 | | 2.1 | | ✓ | |
| | 2.2 | | VGA:2.2 | | 2.2 | | ✓ | |
| | 2.3 | | VGA:2.3 | | 2.3 | | ✓ | |
| | 2.4 | | VGA:2.4 | | 2.4 | | ✓ | |
| | 2.5 | | VGA:2.5 | | 2.5 | | ✓ | |
| | 2.6 | | VGA:2.6 | | 2.6 | | ✓ | |
| | 2.7 | | VGA:2.7 | | 2.7 | | ✓ | |
| | 2.8 | | VGA:2.8 | | 2.8 | | ✓ | |
| | USER1 | | VGA:US1 | | US1 | | ✓ | |
| | USER2 | | VGA:US2 | | US2 | | ✓ | |
| | DICOM | | VGA:DIC | | DIC | | ✓ | |
| | HDR HLG | | VGA:HD1 | | HD1 | | ✓ | |
| | HDR ST2048-500 | | VGA:HD2 | | HD2 | | ✓ | |
| | HDR ST2048-1000 | | VGA:HD3 | | HD3 | | ✓ | |
| | DEFAULT | | VGA:DEF | | DEF | | ✓ | |
| GAMMA-HDR HLG SYSTEM GAMMA | min. | (0.1step) | VXX:HLGS1=+1.00 | QVX:HLGS1 | HLGS1=1.00 | | ✓ | |
| | max. | | VXX:HLGS1=+1.62 | | HLGS1=1.62 | | ✓ | |
| GAMMA-NAME SETTING USER1 | GAMMAUSER1 | | VXX:NCGS2=GAMMAUSER1 | QVX:NCGS2 | NCGS2=GAMMAUSER1 | | ✓ | |
| GAMMA-NAME SETTING USER2 | GAMMAUSER2 | | VXX:NCGS4=GAMMAUSER2 | QVX:NCGS4 | NCGS4=GAMMAUSER2 | | ✓ | |
| GAMMA-NAME CLEAR USER1 | GAMMAUSER1 | | VXX:NCLI2=+00000 | | | | ✓ | |
| GAMMA-NAME CLEAR USER2 | GAMMAUSER2 | | VXX:NCLI4=+00000 | | | | ✓ | |
| DAYLIGHT VIEW FRONT INSTALL | OFF | | VXX:DLVI0=+00000 | QVX:DLVI0 | DLVI0=+00000 | | ✓ | |
| | AUTO(1) | | VXX:DLVI0=+00001 | | DLVI0=+00001 | | ✓ | |

| CATEGORY | FUNCTION | Parameter/Name | Sub-Parameter | CONTROL | | QUERY | | FRQ50 SERIES | | | |
|----------------------------|---|-------------------------------------|--------------------------------------|--|--|--|--|--|--|--|----------------------------|
| | | | | COMMANDS/CALL BACK | COMMANDS | CALL BACK | FRQ60 | | | | |
| | GEOMETRY - FREE GRID - CONTROL POINTS COLOR | WHITE | | VXX:GMGI8=+00001 | QVX:GMGI8 | GMGI8=+00001 | | ✓ | | | |
| | | BLACK | | VXX:GMGI8=+00002 | | GMGI8=+00002 | | ✓ | | | |
| | | RED | | VXX:GMGI8=+00003 | | GMGI8=+00003 | | ✓ | | | |
| | | GREEN | | VXX:GMGI8=+00004 | | GMGI8=+00004 | | ✓ | | | |
| | | BLUE | | VXX:GMGI8=+00005 | | GMGI8=+00005 | | ✓ | | | |
| | | CYAN | | VXX:GMGI8=+00006 | | GMGI8=+00006 | | ✓ | | | |
| | | MAGENTA | | VXX:GMGI8=+00007 | | GMGI8=+00007 | | ✓ | | | |
| | | YELLOW | | VXX:GMGI8=+00008 | | GMGI8=+00008 | | ✓ | | | |
| | | CONVERGENCE | OFF ON | | VXX:CNVI1=+00000 VXX:CNVI1=+00001 | QVX:CNVI1 | CNVI1=+00000 CNVI1=+00001 | | ✓ ✓ | | |
| | CONVERGENCE - UPPER LEFT VERTICAL | | | VXX:CNVS2=*:***** VXX:CNVS2=R:***** VXX:CNVS2=G:***** VXX:CNVS2=B:***** VXX:CNVS2=*:+00.00 VXX:CNVS2=*:+03.75 | QVX:CNVS2 | CNVS2=*:***** CNVS2=R:***** CNVS2=G:***** CNVS2=B:***** CNVS2=*:+00.00 CNVS2=*:+03.75 | | ✓ ✓ ✓ ✓ ✓ ✓ | | | |
| | | CONVERGENCE - UPPER LEFT HORIZONTAL | | | VXX:CNVS3=*:***** VXX:CNVS3=R:***** VXX:CNVS3=G:***** VXX:CNVS3=B:***** VXX:CNVS3=*:+00.00 VXX:CNVS3=*:+03.75 | QVX:CNVS3 | CNVS3=*:***** CNVS3=R:***** CNVS3=G:***** CNVS3=B:***** CNVS3=*:+00.00 CNVS3=*:+03.75 | | ✓ ✓ ✓ ✓ ✓ ✓ | | |
| | | | CONVERGENCE - UPPER RIGHT VERTICAL | | | VXX:CNVS4=*:***** VXX:CNVS4=R:***** VXX:CNVS4=G:***** VXX:CNVS4=B:***** VXX:CNVS4=*:+00.00 VXX:CNVS4=*:+03.75 | QVX:CNVS4 | CNVS4=*:***** CNVS4=R:***** CNVS4=G:***** CNVS4=B:***** CNVS4=*:+00.00 CNVS4=*:+03.75 | | ✓ ✓ ✓ ✓ ✓ ✓ | |
| | | | | CONVERGENCE - UPPER RIGHT HORIZONTAL | | | VXX:CNVS5=*:***** VXX:CNVS5=R:***** VXX:CNVS5=G:***** VXX:CNVS5=B:***** VXX:CNVS5=*:+00.00 VXX:CNVS5=*:+03.75 | QVX:CNVS5 | CNVS5=*:***** CNVS5=R:***** CNVS5=G:***** CNVS5=B:***** CNVS5=*:+00.00 CNVS5=*:+03.75 | | ✓ ✓ ✓ ✓ ✓ ✓ |
| | | | | | CONVERGENCE - LOWER LEFT VERTICAL | | | VXX:CNVS6=*:***** VXX:CNVS6=R:***** VXX:CNVS6=G:***** VXX:CNVS6=B:***** VXX:CNVS6=*:+00.00 VXX:CNVS6=*:+03.75 | QVX:CNVS6 | CNVS6=*:***** CNVS6=R:***** CNVS6=G:***** CNVS6=B:***** CNVS6=*:+00.00 CNVS6=*:+03.75 | |
| | CONVERGENCE - LOWER LEFT HORIZONTAL | | | | | | | VXX:CNVS7=*:***** VXX:CNVS7=R:***** VXX:CNVS7=G:***** VXX:CNVS7=B:***** VXX:CNVS7=*:+00.00 VXX:CNVS7=*:+03.75 | QVX:CNVS7 | CNVS7=*:***** CNVS7=R:***** CNVS7=G:***** CNVS7=B:***** CNVS7=*:+00.00 CNVS7=*:+03.75 | |
| | | CONVERGENCE - LOWER RIGHT VERTICAL | | | | | | VXX:CNVS8=*:***** VXX:CNVS8=R:***** VXX:CNVS8=G:***** VXX:CNVS8=B:***** VXX:CNVS8=*:+00.00 VXX:CNVS8=*:+03.75 | QVX:CNVS8 | CNVS8=*:***** CNVS8=R:***** CNVS8=G:***** CNVS8=B:***** CNVS8=*:+00.00 CNVS8=*:+03.75 | |
| | | | CONVERGENCE - LOWER RIGHT HORIZONTAL | | | | | VXX:CNVS9=*:***** VXX:CNVS9=R:***** VXX:CNVS9=G:***** VXX:CNVS9=B:***** VXX:CNVS9=*:+00.00 VXX:CNVS9=*:+03.75 | QVX:CNVS9 | CNVS9=*:***** CNVS9=R:***** CNVS9=G:***** CNVS9=B:***** CNVS9=*:+00.00 CNVS9=*:+03.75 | |
| | | | | SHIFT-HORIZONTAL | | 0 +4095 | | VTH:0000 VTH:4095 | QTH | 0000 4095 | |
| | | | | | SHIFT-VERTICAL | 0 +4094 | | VTV:0000 VTV:4094 | QTV | 0000 4094 | |
| | CLOCK PHASE | | | 0 +31 | | | VCP:000 VCP:031 | QCP | 000 063 | | ✓ ✓ |
| | | ASPECT | | AUTO/VID AUTO/DEFAULT | | VSE:0 | QSE | 0 | | ✓ | |
| | NORMAL(4:3) | | | VSE:1 | | 1 | | ✓ | | | |
| | WIDE(16:9) | | | VSE:2 | | 2 | | ✓ | | | |
| | NATIVE(through) | | | VSE:5 | | 5 | | ✓ | | | |
| | FULL(HV FIT) | | | VSE:6 | | 6 | | ✓ | | | |
| | H-FIT | | | VSE:9 | | 9 | | ✓ | | | |
| | V-FIT | | | VSE:10 | | 10 | | ✓ | | | |
| | ZOOM-HORIZONTAL | 50 999 | | OZH:050 OZH:999 | QZH | 050 999 | | ✓ ✓ | | | |
| | | ZOOM-VERTICAL | 50 999 | | OZV:050 OZV:999 | QZV | 050 999 | | ✓ ✓ | | |
| | ZOOM-BOTH | | 50 999 | | OZO:050 OZO:999 | QZO | 050 999 | | ✓ ✓ | | |
| | | ZOOM-INTERLOCKED | OFF ON | | OZS:0 OZS:1 | QZS | 0 1 | | ✓ ✓ | | |
| | ZOOM-MODE | | INTERNAL FULL | | OZT:0 OZT:1 | QZT | 0 1 | | ✓ ✓ | | |
| | | DIGITAL CINEMA REALITY | AUTO | | OPD:0 | QPD | 0 | | ✓ | | |
| | OFF | | | OPD:1 | | 1 | | ✓ | | | |
| | 30p/25p FIXED | | | OPD:2 | | 2 | | ✓ | | | |
| | BLANKING-UPPER | | min. max. | | DBU:000 DBU:2398 | QLU | 000 2398 | | 0 2398 | | |
| | BLANKING-LOWER | min. max. | | DBB:000 DBB:2398 | QLB | 000 2398 | | 0 2398 | | | |
| | | BLANKING-RIGHT | min. max. | | DBR:000 DBR:3838 | QLR | 000 3838 | | 0 3838 | | |
| | BLANKING-LEFT | | min. max. | | DBL:000 DBL:3838 | QLL | 000 3838 | | 0 3838 | | |
| | | INPUT RESOLUTION-TOTAL DOTS | 330 4095 | | VTD:0330 VTD:4095 | QTD | 0330 4095 | | ✓ ✓ | | |
| | INPUT RESOLUTION-DISPLAY DOTS | | 300 4065 | | VDD:0300 VDD:4065 | QDD | 0300 4065 | | ✓ ✓ | | |
| | | INPUT RESOLUTION-TOTAL LINES | 155 2047 | | VTL:0155 VTL:2047 | QTL | 0155 2047 | | ✓ ✓ | | |
| | INPUT RESOLUTION-DISPLAY LINES | | 150 2037 | | VDL:0150 VDL:2037 | QDL | 0150 2037 | | ✓ ✓ | | |
| | | CLAMP POSITION | 1 255 | | VLT:001 VLT:255 | QLT | 001 255 | | ✓ ✓ | | |
| | CUSTOM MASKING * | | OFF | | VXX:MSKI1=+00000 | QVX:MSKI1 | MSKI1=+00000 | | ✓ | | |
| | | PC-1 | | VXX:MSKI1=+00001 | | MSKI1=+00001 | | ✓ | | | |
| | | PC-2 | | VXX:MSKI1=+00002 | | MSKI1=+00002 | | ✓ | | | |
| | | PC-3 | | VXX:MSKI1=+00003 | | MSKI1=+00003 | | ✓ | | | |
| | EDGE BLENDING | OFF | | VXX:EDBI0=+00000 | QVX:EDBI0 | EDBI0=+00000 | | ✓ | | | |
| | | ON | | VXX:EDBI0=+00001 | | EDBI0=+00001 | | ✓ | | | |
| USER | | | VXX:EDBI0=+00002 | | EDBI0=+00002 | | ✓ | | | | |
| EDGE BLENDING-UPPER ON/OFF | OFF ON | | VGU:0 VGU:1 | QGU | 0 1 | | ✓ ✓ | | | | |
| | EDGE BLENDING-LOWER ON/OFF | OFF ON | | VGB:0 VGB:1 | QGB | 0 1 | | ✓ ✓ | | | |
| EDGE BLENDING-LEFT ON/OFF | | OFF ON | | VGL:0 VGL:1 | QGL | 0 1 | | ✓ ✓ | | | |
| | EDGE BLENDING-RIGHT ON/OFF | OFF ON | | VGR:0 VGR:1 | QGR | 0 1 | | ✓ ✓ | | | |
| EDGE BLENDING-START-UPPER | | min. | | VEU:0000 | QEU | 0000 | | 0 | | | |

| CATEGORY | FUNCTION | Parameter/Name | Sub-Parameter | CONTROL | | QUERY | | FRQ50 SERIES |
|----------|--|--|---------------|--|--------------|--|-------|--------------|
| | | | | COMMANDS/CALL BACK | COMMANDS | CALL BACK | FRQ60 | |
| | NO SIGNAL SHUT-OFF | INPIT10 | | VXX:SISI2=+00010 | | SISI2=+00010 | | ✓ |
| | DISABLE | DISABLE | | OAF:00 | QAF | 00 | | ✓ |
| | 10min | 10min | | OAF:10 | | 10 | | ✓ |
| | 20min | 20min | | OAF:20 | | 20 | | ✓ |
| | 30min | 30min | | OAF:30 | | 30 | | ✓ |
| | 40min | 40min | | OAF:40 | | 40 | | ✓ |
| | 50min | 50min | | OAF:50 | | 50 | | ✓ |
| | 60min | 60min | | OAF:60 | | 60 | | ✓ |
| | 70min | 70min | | OAF:70 | | 70 | | ✓ |
| | 80min | 80min | | OAF:80 | | 80 | | ✓ |
| | 90min | 90min | | ODR:90 | | 90 | | ✓ |
| | NO SIGNAL LIGHTS-OUT | DISABLE | | VXX:SLOI1=+00000 | QVX:SLOI1 | SLOI1=+00000 | | ✓ |
| | 10SEC. | 10SEC. | | VXX:SLOI1=+00010 | | SLOI1=+00010 | | ✓ |
| | 20SEC. | 20SEC. | | VXX:SLOI1=+00020 | | SLOI1=+00020 | | ✓ |
| | 30SEC. | 30SEC. | | VXX:SLOI1=+00030 | | SLOI1=+00030 | | ✓ |
| | 1MIN. | 1MIN. | | VXX:SLOI1=+00060 | | SLOI1=+00060 | | ✓ |
| | 2MIN. | 2MIN. | | VXX:SLOI1=+00120 | | SLOI1=+00120 | | ✓ |
| | 3MIN. | 3MIN. | | VXX:SLOI1=+00180 | | SLOI1=+00180 | | ✓ |
| | 5MIN. | 5MIN. | | VXX:SLOI1=+00300 | | SLOI1=+00300 | | ✓ |
| | NO SIGNAL SETTING - FUNCTION BUTTON | OFF | | VXX:SINS1=OFF | QVX:SINS1 | SINS1=OFF | | ✓ |
| | DISABLE | DISABLE | | OFC:0 | QFC | 0 | | ✓ |
| | SYSTEM SELECTOR | SYSTEM SELECTOR | | OFC:1 | | 1 | | ✓ |
| | SYSTEM DAYLIGHT VIEW | SYSTEM DAYLIGHT VIEW | | OFC:2 | | 2 | | ✓ |
| | SUB MEMORY | SUB MEMORY | | OFC:3 | | 3 | | ✓ |
| | FREEZE | FREEZE | | OFC:4 | | 4 | | ✓ |
| | WAVEFORM MONITOR | WAVEFORM MONITOR | | OFC:6 | | 6 | | ✓ |
| | PROJECTION METHOD | PROJECTION METHOD | | OFC:10 | | 10 | | ✓ |
| | GEOMETRY | GEOMETRY | | OFC:13 | | 13 | | ✓ |
| | OSD POSITION | OSD POSITION | | OFC:14 | | 14 | | ✓ |
| | DATE AND TIME-DATE SETTING | Year: yyyy Month: mm Date: dd Day:w(1~7:Mon~Sun) | | TSD:201506151 TSD:yyyymmddw | QGD | 201506161 yyyymmddw | | ✓ |
| | DATE AND TIME-TIME SETTING | Hour: hh Minute: mm Second: ss | | TST:154503 TST:hmmss | QGT | 154503 hmmss | | ✓ |
| | DATE AND TIME-NTP SYNCHRONIZATION | OFF ON | | VXX:NTPIO=+00000 VXX:NTPIO=+00001 | QVX:NTPIO | NTPIO=+00000 NTPIO=+00001 | | ✓ |
| | INITIALIZE-ALL USER DATA | USER INITILIZE USER RESTORE | | VXX:RSTS1=0password VXX:RSTS1=1password | | | | ✓ |
| | INITIAL START UP | STANDBY ON LAST MEMORY | | OPY:0 OPY:1 OPY:2 | QPY | 0 1 2 | | ✓ |
| | AUDIO SETTING-VOLUME | 0 63 | | AVL:000 AVL:063 | QAV | 000 063 | | ✓ |
| | AUDIO SETTING-BALANCE | -16 16 | | ABL:-16 ABL:016 | QBL | -16 16 | | ✓ |
| | AUDIO SETTING-IN STANDBY MODE | OFF ON | | VXX:ASBIO=+00000 VXX:ASBIO=+00001 | QVX:ASBIO | ASBIO=+00000 ASBIO=+00001 | | ✓ |
| | AUDIO SETTING-IN SHUTTER MODE | OFF ON | | VXX:ASHI1=+00000 VXX:ASHI1=+00001 | QVX:ASHI1 | ASHI1=+00000 ASHI1=+00001 | | ✓ |
| | AUDIO SETTING-AUDIO IN SELECT-COMPUTER1 | AUDIO IN 1 AUDIO IN 2 AUDIO IN 3 | | VXX:AINI0=+00000 VXX:AINI0=+00001 VXX:AINI0=+00002 | QVX:AINI0 | AINI0=+00000 AINI0=+00001 AINI0=+00002 | | ✓ |
| | AUDIO SETTING-AUDIO IN SELECT-COMPUTER2 | AUDIO IN 1 AUDIO IN 2 AUDIO IN 3 | | VXX:AINI1=+00000 VXX:AINI1=+00001 VXX:AINI1=+00002 | QVX:AINI1 | AINI1=+00000 AINI1=+00001 AINI1=+00002 | | ✓ |
| | AUDIO SETTING-AUDIO IN SELECT-HDMI1 | HDMI1 AUDIO IN AUDIO IN 1 AUDIO IN 2 AUDIO IN 3 | | VXX:AINI3=+00003 VXX:AINI3=+00000 VXX:AINI3=+00001 VXX:AINI3=+00002 | QVX:AINI3 | AINI3=+00003 AINI3=+00000 AINI3=+00001 AINI3=+00002 | | ✓ |
| | AUDIO SETTING-AUDIO IN SELECT-VIDEO | AUDIO IN 1 AUDIO IN 2 AUDIO IN 3 | | VXX:AINI4=+00000 VXX:AINI4=+00001 VXX:AINI4=+00002 | QVX:AINI4 | AINI4=+00000 AINI4=+00001 AINI4=+00002 | | ✓ |
| | AUDIO SETTING-AUDIO IN SELECT-HDMI2 | HDMI2 AUDIO IN AUDIO IN 1 AUDIO IN 2 AUDIO IN 3 | | VXX:AINI7=+00003 VXX:AINI7=+00000 VXX:AINI7=+00001 VXX:AINI7=+00002 | QVX:AINI7 | AINI7=+00003 AINI7=+00000 AINI7=+00001 AINI7=+00002 | | ✓ |
| | AUDIO SETTING-AUDIO IN SELECT-DIGITAL LINK | DIGITAL LINK AUDIO IN AUDIO IN 1 AUDIO IN 2 AUDIO IN 3 | | VXX:AINI8=+00005 VXX:AINI8=+00000 VXX:AINI8=+00001 VXX:AINI8=+00002 | QVX:AINI8 | AINI8=+00005 AINI8=+00000 AINI8=+00001 AINI8=+00002 | | ✓ |
| | MODEL NAME | MODEL NAME | | | QID | MODELNAME | | ✓ |
| | SERIAL NUMBER | SW0101234 | | | QSN | SW0101234 | | ✓ |
| | PROJECTOR RUNTIME | 7864320H | | | QVX:RTMS1 | RTMS1=7864320 | | ✓ |
| | LAMP1(LIGHT1) RUNTIME | 9999H | | | Q\$1:1 | 9999 | | ✓ |
| | LIGHT1 RUNTIME | 7864320H | | | QVX:LRTS3=00 | LRTS3=00:7864320 | | ✓ |
| | LIGHT STATUS | ALL OFF 1:ON, 2:OFF | | | QLS | 0 1 | | ✓ |
| | LAMP(LIGHT) CONTROL STATUS | LAMP OFF In turning ON LAMP ON LAMP Cooling | | | Q\$S | 0 1 2 3 | | ✓ |
| | POWER STATUS | POWER OFF In turning ON POWER ON Cooling | | | QVX:POWI1 | POWI1=+00001 POWI1=+00002 POWI1=+00003 POWI1=+00004 | | ✓ |
| | MAC ADDRESS | AB0102030405 | | | QMA | AB0102030405 | | ✓ |
| | MAIN FIRMWARE VERSION | V1.00.01 | | | QVX:SVRS0 | SVRS0=1.00.01 | | ✓ |
| | NETWORK FIRMWARE VERSION | V1.00 | | | QVX:SVRS1 | SVRS1=1.00 | | ✓ |
| | SUB FIRMWARE VERSION | V1.00.01 | | | QVX:SVRS2 | SVRS2=1.00.01 | | ✓ |
| | INPUT SIGNAL NAME | CHANNEL1 (MAIN CH) | | | QVX:NSGS1 | NSGS1=*****..... | | ✓ |
| | TEMPERATURE (INTAKE) | 0030/0080 | | | QTM:0 | 0030/0080 | | ✓ |
| | TEMPERATURE (EXHAUST AIR) | 0030/0080 | | | QTM:1 | 0030/0080 | | ✓ |
| | TEMPERATURE (OPTICS MODULE) | 0030/0080 | | | QTM:2 | 0030/0080 | | ✓ |
| | TEMPERATURE (LIGHT1 / LIGHT1- | 0030/0080 | | | QTM:11 | 0030/0080 | | ✓ |
| | TEMPERATURE (LIGHT2 / LIGHT1- | 0030/0080 | | | QTM:12 | 0030/0080 | | ✓ |
| | LAN data Cloning Write protect | OFF ON | | LCL:WRP0 LCL:WRP1 | QCL:WRP | QCL:WRP0 QCL:WRP1 | | ✓ |
| | HDMI-CEC | OFF ON | | SHC:FNC0 SHC:FNC1 | QHC:FNC | QHC:FNC0 QHC:FNC1 | | ✓ |
| | HDMI-CEC HDMI1 (Change Device) | NEXT PREVIEW | | SHC:MH1NXT SHC:MH1PRE | | | | ✓ |
| | HDMI-CEC HDMI1 (Get Device) | DEVICE NAME | | | QHC:HM1 | QHC:HM1DEVICENAME | | ✓ |
| | HDMI-CEC HDMI2 (Change Device) | NEXT PREVIEW | | SHC:MH2NXT SHC:MH2PRE | | | | ✓ |
| | HDMI-CEC HDMI2 (Get Device) | DEVICE NAME | | | QHC:HM2 | QHC:HM2DEVICENAME | | ✓ |
| | HDMI-CEC - MENU CODE | 0x09 (ROOT) 0x0A (SETUP) 0x0B (CONTENTS) 0x0C (FAVORITE) 0x10 (MEDIA TOP) 0x11 (MEDIA POP UP) | | SHC:MNC1 SHC:MNC2 SHC:MNC3 SHC:MNC4 SHC:MNC5 SHC:MNC6 | QHC:MNC | QHC:MNC1 QHC:MNC2 QHC:MNC3 QHC:MNC4 QHC:MNC5 QHC:MNC6 | | ✓ |
| | HDMI-CEC - PROJECTOR -> | DISABLE POWER OFF POWER ON/OFF | | SHC:PTSOFF SHC:PTSPWF SHC:PTSPWR | QHC:PTS | QHC:PTSOFF QHC:PTSPWF QHC:PTSPWR | | ✓ |
| | HDMI-CEC - DEVICE -> | DISABLE POWER ON | | SHC:STPOFF SHC:STPPON | QHC:STP | QHC:STPOFF QHC:STPPON | | ✓ |

| CATEGORY | FUNCTION | Parameter/Name | Sub-Parameter | CONTROL | | QUERY | | FRQ50 SERIES |
|-------------------------------|--|------------------------|------------------|----------------------|--------------|--------------------------|-------|--------------|
| | | | | COMMANDS/CALL BACK | COMMANDS | CALL BACK | FRQ60 | |
| | | POWER ON/OFF | | SHC:STPPWR | | QHC:STPPWR | | ✓ |
| TEST PATTERN | TEST PATTERN | Off | | OTS:00 | QTS | 00 | | ✓ |
| | | White | | OTS:01 | | 01 | | ✓ |
| | | Black | | OTS:02 | | 02 | | ✓ |
| | | Window | | OTS:05 | | 05 | | ✓ |
| | | Reversed Window | | OTS:06 | | 06 | | ✓ |
| | | Cross Hatch | | OTS:07 | | 07 | | ✓ |
| | | Color Bar V | | OTS:08 | | 08 | | ✓ |
| | | Convergence | | OTS:11 | | 11 | | ✓ |
| | | Color Bar Side | | OTS:51 | | 51 | | ✓ |
| | | 16:9/4:3 | | OTS:59 | | 59 | | ✓ |
| | | Focus Red | | OTS:70 | | 70 | | ✓ |
| | | Focus Green | | OTS:71 | | 71 | | ✓ |
| | | Focus Blue | | OTS:72 | | 72 | | ✓ |
| | | Focus Cyan | | OTS:73 | | 73 | | ✓ |
| | | Focus Magenta | | OTS:74 | | 74 | | ✓ |
| Focus Yellow | | OTS:75 | | 75 | | ✓ | | |
| Focus | | OTS:78 | | 78 | | ✓ | | |
| SIGNAL LIST | SIGNAL LIST-REGISTRATION | | | OEM | | | | ✓ |
| | SIGNAL LIST-DELETE | A1 | | ODM:A1 | | | | ✓ |
| | | A2 | | ODM:A2 | | | | ✓ |
| | | A7 | | ODM:A7 | | | | ✓ |
| | | A8 | | ODM:A8 | | | | ✓ |
| | | L1 | | ODM:L1 | | | | ✓ |
| | | L2 | | ODM:L2 | | | | ✓ |
| | | L7 | | ODM:L7 | | | | ✓ |
| | | L8 | | ODM:L8 | | | | ✓ |
| | SUB MEMORY LIST-CHANGEVER | 01 | | OCS:01 | | | | ✓ |
| | | 96 | | OCS:96 | | | | ✓ |
| | SUB MEMORY LIST-CHANGEVER (EXTENDED) | 01 | | OCS:01-01 | | | | ✓ |
| 96 | | | OCS:95-96 | | | | ✓ | |
| SUB MEMORY LIST-REGISTRATION | | | OES | | | | ✓ | |
| SUB MEMORY LIST-DELETE | 01 | | ODS:01-01 | | | | ✓ | |
| | 96 | | ODS:95-96 | | | | ✓ | |
| SUB MEMORY USAGE STATE | 01 | | | QSB | 01 | | ✓ | |
| | 96 | | | | 96 | | ✓ | |
| SECURITY | SECURITY SETTING | OFF | | | QVX:SPWI1 | SPWI1+=00000 | | ✓ |
| | | ON | | | | SPWI1+=00001 | | ✓ |
| | CONTROL DEVICE SETUP-CONTROL PANEL | DISABLE | | VXX:CDSI1+=00000 | QVX:CDSI1 | CDSI1+=00000 | | ✓ |
| | | ENABLE | | VXX:CDSI1+=00001 | | CDSI1+=00001 | | ✓ |
| | | USER | | VXX:CDSI1+=00002 | | CDSI1+=00002 | | ✓ |
| | CONTROL DEVICE SETUP-REMOTE CONTROL | DISABLE | | VXX:CDSI2+=00000 | QVX:CDSI2 | CDSI2+=00000 | | ✓ |
| ENABLE | | | VXX:CDSI2+=00001 | | CDSI2+=00001 | | ✓ | |
| USER | | | VXX:CDSI2+=00002 | | CDSI2+=00002 | | ✓ | |
| NETWORK | WIRELESS LAN | OFF(DISABLE) | | ONS:0 | QVX:WLSI1 | WLSI1+=00000 | | ✓ |
| | | ON(ENABLE) | | ONS:14 | | WLSI1+=00014 | | ✓ |
| | DIGITAL LINK MODE | AUTO | | VXX:DKMI1+=00001 | QVX:DKMI1 | DKMI1+=00001 | | ✓ |
| | | DIGITAL LINK | | VXX:DKMI1+=00002 | | DKMI1+=00002 | | ✓ |
| | | ETHERNET | | VXX:DKMI1+=00003 | | DKMI1+=00003 | | ✓ |
| | | LONG REACH MODE | | VXX:DKMI1+=00004 | | DKMI1+=00004 | | ✓ |
| | DIGITAL LINK STATUS-LINK | NO LINK | | | QVX:DKSI1 | DKSI1+=00000 | | ✓ |
| | | DIGITAL LINK | | | | DKSI1+=00001 | | ✓ |
| | | LPM | | | | DKSI1+=00002 | | ✓ |
| | | ETHERNET | | | | DKSI1+=00003 | | ✓ |
| | DIGITAL LINK STATUS-HDCP STATUS | NO SIGNAL | | | QVX:DKSI2 | DKSI2+=00000 | | ✓ |
| | | OFF | | | | DKSI2+=00001 | | ✓ |
| | | ON | | | | DKSI2+=00002 | | ✓ |
| | DIGITAL LINK STATUS-SIGNAL QUALITY (MIN) | -255 | | | QVX:DKSI3 | DKSI3=-00255 | | ✓ |
| | | 0 | | | | DKSI3+=00000 | | ✓ |
| | DIGITAL LINK STATUS-SIGNAL QUALITY (MAX) | -255 | | | QVX:DKSI4 | DKSI4=-00255 | | ✓ |
| | | 0 | | | | DKSI4+=00000 | | ✓ |
| | DIGITAL LINK INPUT CH LIST | HD1:HDMI1,HD2:HDMI2... | | | QVX:DLIS1 | DLIS1=HD1:HDMI1,****:*** | | ✓ |
| | PROJECTOR NAME SETTING | PROJECTOR1 | | VXX:NCGS8=PROJECTOR1 | QVX:NCGS8 | NCGS8=PROJECTOR1 | | ✓ |
| | Art-Net SETUP | OFF | | VXX:DANI1+=00000 | QVX:DANI1 | DANI1+=00000 | | ✓ |
| ON(2.*.*) | | | VXX:DANI1+=00002 | | DANI1+=00002 | | ✓ | |
| ON(10.*.*) | | | VXX:DANI1+=00003 | | DANI1+=00003 | | ✓ | |
| ON(MANUAL) | | | VXX:DANI1+=00004 | | DANI1+=00004 | | ✓ | |
| Art-Net SETUP-START ADDRESS | 1 | | VXX:DANI3+=00001 | QVX:DANI3 | DANI3+=00001 | | ✓ | |
| | 501 | | VXX:DANI3+=00501 | | DANI3+=00501 | | ✓ | |
| Art-Net SETUP-NET | 0 | | VXX:DANI4+=00000 | QVX:DANI4 | DANI4+=00000 | | ✓ | |
| | 127 | | VXX:DANI4+=00127 | | DANI4+=00127 | | ✓ | |
| Art-Net SETUP-SUB NET | 0 | | VXX:DANI5+=00000 | QVX:DANI5 | DANI5+=00000 | | ✓ | |
| | 15 | | VXX:DANI5+=00015 | | DANI5+=00015 | | ✓ | |
| Art-Net SETUP-UNIVERS | 0 | | VXX:DANI6+=00000 | QVX:DANI6 | DANI6+=00000 | | ✓ | |
| | 15 | | VXX:DANI6+=00015 | | DANI6+=00015 | | ✓ | |
| Art-Net SETUP-CHANNEL SETTING | DEFAULT | | VXX:DANI8+=00000 | QVX:DANI8 | DANI8+=00000 | | ✓ | |
| | 1 | | VXX:DANI8+=00001 | | DANI8+=00001 | | ✓ | |
| | 2 | | VXX:DANI8+=00002 | | DANI8+=00002 | | ✓ | |
| | USER | | VXX:DANI8+=00100 | | DANI8+=00100 | | ✓ | |
| PRESHOW MODE | OFF | | | QVX:PSMI1 | PSMI1+=00000 | | ✓ | |
| | ON | | | | PSMI1+=00001 | | ✓ | |

Note: The commands or parameters with "*" shows available commands or parameters for the projector which has been activated by the Upgrade Kit.